


Service Manual

Professional Hair Clipper

Model No. **ER-GC33**



Africa
Middle East

⚠ WARNING

This service information is designed for experienced repair technicians only and is not designed for use by the general public. It does not contain warnings or cautions to advise non-technical individuals of potential dangers in attempting to service a product. Products powered by electricity should be serviced or repaired only by experienced professional technicians. Any attempt to service or repair the product or products dealt with in this service information by anyone else could result in serious injury or death.

IMPORTANT SAFETY NOTICE

There are special components used in this equipment which are important for safety. These parts are marked by \triangle in the Schematic Diagrams, Circuit Board Diagrams, Exploded Views and Replacement Parts List. It is essential that these critical parts should be replaced with manufacturer's specified parts to prevent shock, fire or other hazards. Do not modify the original design without permission of manufacturer.

TABLE OF CONTENTS

	PAGE		PAGE
1 Warning	2		
2 Specifications	2		
3 Troubleshooting Guide	3		
4 Disassembly and Assembly Instructions	4		
4.1. Disassembly Instructions	4		
4.2. Assembly Instructions	5		
5 Wiring Connection Diagram	6		
6 Schematic Diagram	6		
7 Exploded View and Replacement Parts List	7		

Panasonic®

© Panasonic Corporation 2008 Unauthorized copying and distribution is a violation of law.

1 Warning

Caution:


- Pb free solder has a higher melting point than standard solder; Typically the melting point is 50 - 70°F (30 - 40°) higher. Please use a soldering iron with temperature control and adjust it to $750 \pm 20^{\circ}\text{F}$ ($400 \pm 10^{\circ}$). In case of using high temperature soldering iron, please be careful not to heat too long.
- Pb free solder will tend to splash when heated too high (about 1100°F / 600°C).

2 Specifications

Power source	AC 100-240V, 50-60Hz
Motor voltage	1.2V DC
Charging time	8 hours
Rated usable time with full-charging	40 minutes
Weight	Approx. 180g (Main body) Approx. 170g (Adaptor)
Supplied accessories	1-2mm comb attachment 3-4mm comb attachment 5-6mm comb attachment Comb attachment for underarm (Only for ER-GC33) Cleaning brush Oil

3 Troubleshooting Guide


(Refer to Wiring Connection Diagram)



4 Disassembly and Assembly Instructions


4.1. Disassembly Instructions

1. Take out blade.
2. Loosen two screws at right and left side of springs and two screws on housing B.
3. To separate housing A and B with care for preventing breakage of hooks.
4. Take out motor from housing A.
5. Remove module assembly.
6. Remove switch handle.



4.2. Assembly Instructions

1. Assemble module block and motor into housing A.
Make sure of a position to be set "○" with both switch handle and switch contact at the rear side of module.
2. Confirm module block or motor to be set into housing A firmly, and then check its operation with connecting adaptor.
3. Assemble housing A and B with care for breakage of housing, and tighten four screws.



5 Wiring Connection Diagram







Fig.2

6 Schematic Diagram



7 Exploded View and Replacement Parts List

7.1. Exploded View for ER-GC33



7.2. Replacement Parts List for ER-GC33

Safety	Ref. No.	Part No.	Part Name & Description	Quantity	Remarks
	1	WERGC33K7458	COMB ATTACHMENT	1	1-2mm
	2	WERGC33K7468	COMB ATTACHMENT	1	3-4mm
	3	WERGC33K7478	COMB ATTACHMENT	1	5-6mm
	4	WERGC33K7488	EPILATION HEAD FRAME	1	
	5	WER9730E	BLADE BLOCK	1	
	6	WERGC33K3108	SWITCH HANDLE	1	
	7	WERGC33K3118	CONNECTING PLATE	1	
	8	WERGC33K3058	HOUSING A	1	
	9	WERGC33K3068	HOUSING B	1	
	10	WER240B0166	BLADE MOUNTING SPRING	2	
	11	WERGC33K9008	SCREW	4	K2-8
	12	WERGC33L2108	MODULE ASSEMBLY	1	
	13	WERGC33L2508	RECHARGEABLE BATTERY	1	Ni-MH TYPE
	14	WERGC33L1008	MOTOR	1	
	15	WERGC33K7670	ADAPTOR	1	BF-3 PLUG
	15	WERGC33K7675	ADAPTOR	1	C2 PLUG
	16	WERGC20X7918	OIL	1	
	17	WES76806761	CLEANING BRUSH	1	
-	WERGC33K8008	INDIVIDUAL BOX		1	
-	WERGC33K8009	INDIVIDUAL BOX		1	only for Middle East
-	WERGC33K8108	OPERATING INSTRUCTIONS		1	